

Value+

Non-contact Voltage Detectors

- Safe (Detects voltage without contact)
- Easy to use
- Available with different indicating methods (flashing, sound and vibration)
- Measuring from 90V to 1000V (CAT IV), suitable for a wide range of residential, commercial and industrial needs
- Built-in white torch at the front end for helping to search the testing point in dark (some models)
- Integrated clip design, optimized for pocket storage
- Nice shape
- Auto Power off to enhance the battery life



Non-contact Voltage Detector



Basic Functions	NF11A	NF11B	NF11C	NF11F
AC Voltage	90-1000V	90-1000V	90-1000V	90-1000V
Frequency	40-400Hz	40-400Hz	40-400Hz	40-400Hz
Indicated By				
LED Flashing	✓	✓	✓	✓
Beep Sound (Non-Switchable)		✓		
Beep Sound (Switchable)			✓	✓
Vibrating (Switchable)				✓
On / Off Button		✓	✓	✓
Switch on indication		✓	✓	✓
Auto / Manual Detection Select		✓	✓	✓
Standby Indication	✓	✓	✓	✓
Flashlight		✓		✓
Lower Battery Indicator	✓	✓	✓	✓
Auto Power Off	✓	✓	✓	✓
Overload Protection		CAT IV 1000V		
Powered By		1.5V (AAA) x 2		
Operating Temperature		0°C ~ 40°C		
Storage Temperature		0°C ~ 50°C		
Relative Humidity		< 80%		

* All information provided are subject to change without prior notice.

Futronix Co.

Rm 609 Lee On Industrial Building,
70 Hung To Road, Kwun Tong, Kowloon,
HONG KONG

Tel : (852) 3580 7725

Fax : (852) 3753 4800

e-mail : info@futronix-hk.com



Your Distributor :